


**OPTION-03**

PROJECT:	NORTH:	REFERENCE :	ARCHITECT:
<p>PROPOSED INTERIORS FOR <b>CANARA BANK</b> PANASAPADU BRANCH</p>	<p>ELECTRICAL LAYOUT PLAN GROUND FLOOR</p> 	<p>DESIGN BY : FA DRAWN BY : A.Ahad CHECKED BY: FA SCALE: N T S DATE: 06-06-2024</p>	<p><b>FIROZ AHMED</b> H.NO:13-6-436/A/33, LAKSHMI- APARTMENTS, 2nd FLOOR, 301, LAKSHMI NAGAR, PILLAR NO.68, MEHIDIPATNAM, HYDERABAD, CELL: 98481 49737</p>

S.NO	DESCRIPTION	UNIT	QTY	Rate (Rs)	Amount(Rs)
	<b>INTERNAL ELECTRICAL WORKS</b>				
<b>E - 1</b>	<b>Lights Points(Including Circuit Wiring 2x2.5+1.5 Sqmm)</b>				
	Point Wiring for Light/ Fan/ Exhaust fan with 2runs of 650V grade 1.5 Sq.mm FRLS PVC & 1 run of 1.5 Sq.mm PVC insulated Copper wires , run in 25 mm dia heavy gauge PVC conduits concealed in wall / ceiling conforming to IS including all accessories such as junction boxes, conduit bends elbows and ceiling rose, anodised GI Switch box with modular switch and the box covered with front plate.( Point Wiring Include Circuit Wiring From Main Db to SWitch Board with 2x2.5 +1.5 Sqmm Copper flexible wire etc)				
<b>a</b>	One Light point controlled by one 6A switch.	Nos	32		
<b>b</b>	Two Lights point controlled by one 6A switch.	Nos	8		
<b>c</b>	Exhaust fan point controlled by one switch.	Nos	4		
<b>d</b>	Ceiling fan point controlled by one switch & Electronic Step type Regulator and Concealed MS fan hook box.	Nos	3		
<b>e</b>	Supply and fixing of 6A, 3Pin Socket outlet switches of 6A rating boards for Wall Mounting Fans and (Dependant).	Nos			
<b>i</b>	Independent points	Nos	7		
<b>ii</b>	Dependent points	Nos	7		
<b>d</b>	TV. / Inverter points /Bell point	Nos	8		
<b>E - 2</b>	Supply and Wiring with the following size 650V grade FR PVC insulated Copper conductor wires in suitable <b>PVC conduit</b> including end terminations with suitable lugs.				
	a)Supply and wiring of UPS Points wiring from UPS Room DB to Individual Work Stations With required all Connections and Suitable PVC Conduites. 2runs of 2.5Sq.mm PVC wires with 1run of 1.5 Sq.mm PVC Conduite for UPS out going Wirings	Rmt	86		
	b) 2runs of 4Sq.mm PVC wires with 1run of 2.5 Sq.mm PVC Conduite	Rmt	22		
	c) 2 runs of 6 Sq.mm PVC wires with 1 run of 4 Sq.mm PVC insulated Copper earth wire in PVC in conduit. For A/C Sockets	Rmt	24		
	d) 2runs of 4.0 Sq.mm PVC wires with 1run of 1.5 Sq.mm PVC wire for Name board from the 10 A DP MCB on the main board	LS	1		
<b>E - 3</b>	<b>Light / Fan Fixtures</b>				

S.NO	DESCRIPTION	UNIT	QTY	Rate (Rs)	Amount(Rs)
	Supply and Installation of following type Fluorescent/ Compact fluorescent/ Incandescent light fixtures on wall/ Ceiling including all fixing accessories such as leads, Teak wood round block etc complete as required. The Fluorescent/CFL fixtures shall be complete with Low loss copper ballast PF improvement capacitor, Bipin Rotor type lamp holder, starter, starter base, all prewired upto the terminal block. All fixtures shall be supplied with lamps. The Catalogue Numbers refers to Philips Make or equivalent approved make .				
	a) Recess mounted <b>LED Luminaire</b> 36 x 1W Class LED, Wipro make code: LM - 036 - XXX - WH - XX.				
	Supply	Nos	12		
	Erection	Nos	12		
	Frame	Nos			
	b) Recess mounted <b>LED Down lighter</b> with Pressure die cast aluminium housing (10 x 1W), Wipro make code: LD 49 - 900 - XXX - 60 - XX.				
	Supply	Nos	13		
	Erection	Nos	13		
	c) 20W <b>LED Tube light</b> fixture Wall/ Ceiling mounted (Philips Make TMS 200/140)				
	Supply	Nos	12		
	Erection	Nos	12		
<b>E - 4</b>	<b>Ceiling Fans</b>				
	Supply & Fixing of 1200 mm sweep Crompton Make High Speed Ceiling fan with standard down rod, all accessories Electrical connections. Including fixing materials required.				
	Supply	Nos	3		
	Erection	Nos	3		
<b>E - 5</b>	<b>Wall Mounted Fans</b>				
	Supply & Fixing of 400 mm sweep Wall mounted fan with 3 with metallic body with metallic plates of pin Plug on the lead wire of each fan all accessories Electrical connections. Including fixing materials required.				
	Supply	Nos	7		
	Erection	Nos	7		
<b>E - 6</b>	<b>Exhaust Fans</b>				
	Supply and Installation of heavy duty Exhaust fans with Metallic blades following size sweep with gravity louvres shutters Exhaust fans with Metallic blades of following				
	a) 300mm Sweep (Crompton make Tracent Model)				
	Supply	Nos	3		
	Erection	Nos	3		
<b>E - 7</b>	<b>MAIN DBS / SUB DBS</b>				

S.NO	DESCRIPTION	UNIT	QTY	Rate (Rs)	Amount(Rs)
	Supply Installation Testing and commissioning of TPN MCB Double door Distribution boards dust and vermin protected and rated for 415V, Three Phase AC supply operation including incoming MCB/ELCB as per specifications and required capacity Neutral bar and Earth terminal complete as required and installed in flush with wall including all fixing materials required. MCBs shall conform : 8828 and ELCB /RCCB shall confirm to IS : 12640				
	a)Supply, installation, testing and commissioning of (Double door) with 8Way VTPN MCCB DPX DB with 125A 4Pole MCCB as incomer and 63A TPMCBs -2 Nos, 32A TP MCbs-2 Nos, and 12 nos10/32A SPMCBs s outgoing. (for MAIN DB)	Nos	1		
	b)Supply, installation, testing and commissioning of (Double door) with 4Way TPN MCB DB with 63A 4Pole MCB as incomer and 12 nos10A SPMCBs s outgoing. (for LDB)	Nos	1		
	c)Supply, installation, testing and commissioning of 8way SPN MCB DB (Double door) with 32A DP MCB as incomer and 6nos. 6A/10A/16A SPMCBs as outgoing.(UPS DB)	Nos.	2		
	d)Supply and fixing of 32 A, DP MCB-1No. with encloser for UPS Incoming.	Nos	2		
	e)Supply and fixing of 63A 4 Pole Change over Switch for LDB/UPS Connections with encloser for UPS Incoming.	Nos	1		
<b>E - 8</b>	<b><u>Raw power Wiring and Sockets:</u></b> Supply and wiring of Raw Power Points from Main DB to Individual Work Stations With required all Connections with 2runs of 2.5Sq.mm PVC wires with 1run of 1.5 Sq.mm PVC Conduite for UPS out going Wirings and also SAapply and fixing of 1 <b>Nos 6A</b> sockets with 1 <b>Nos 6A switch</b> of modular type with 'front plate and anodised GI box complete 'as required'.for UPS Sockets	Nos	8		
<b>E - 9</b>	Supply and fixing of 1no 16A 3pin 'socketswith 16A switch of modular type with 'front plate and anodised GI box complete 'as required'.(Raw Power )	Nos	2		
<b>E - 10</b>	<b><u>UPS Wiring and Sockets:</u></b> Supply and wiring of UPS Points from UPS Room DB to Individual Work Stations With required all Connections with 2runs of 2.5Sq.mm PVC wires with 1run of 1.5 Sq.mm PVC Conduite for UPS out going Wirings and also SAapply and fixing of 3 <b>Nos 6A</b> sockets with 2 <b>Nos 6A switch</b> of modular type with 'front plate and anodised GI box complete 'as required'.for UPS Sockets. (UPS -1 conection table / counter no.1,3,5 & 7 and UPS -2 table no. 2,4,6 & 8 etc, and network rack & manager 2 UPS points from UPS-1 & UPS-2.	Nos	10		

S.NO	DESCRIPTION	UNIT	QTY	Rate (Rs)	Amount(Rs)
E - 11	Supply and fixing of 3 Nos 16A sockets with 1 Nos 16A switch of modular type with 'front plate and anodised GI box complete 'as required'.for UPS Sockets	Nos	2		
E -12	Supply installation testing and commissioning of AC Units With 2x4Sqmm+2.5Sqmm Copper Fluxible Wire From Main DB to AC Units including Legrand Make 20A Metal Clad Socket with 25/32A SP MCB set( Like Metal Clad Socket+Wiring From Db to AC Box to Stabilizer to AC Units)	No	4		
E - 13	Supply and erecting of approved make telephone RJ 11Jack for telephone with 2 pair .5mm Thick Telephone cable including pvc conduite with required all materials (RJ-11 Jack+ 2 pair Cable)	Nos	7		
E - 14	Supply and Laying of 10 pair .5mm Thick Telephone cable including pvc conduite with required all materials From Outside to Rack locations	Mts.	56		
E - 15	Supply and fixing of 10 pair Crone Connector box with 10 Pair connectors and required all connections.	Nos	1		
<b>E -16 MV Cables</b>					
	Supply, laying and commissioning of following size 1.1KVgrade PVC insulated armoured aluminium conductor underground cable, in built up cable trench/ 2" PVC pipe or on cable tray with all installation materials.When the cable is to be laid in ground, the same shall be laid at a depth of 750mm below ground level including excavation and refilling of earth after cables are laid,providing protection with sand and bricks at sides and topand cable route markers at 'every 15mtr. interval and also atthe turnings. The cable shall conform to IS 1554/ Part I.Cable protected in 2" Dia G.I Pipe10' long at the pole (correct measurement should be taken by the contractor before procuring the cable.				
	a) 3.5C X 50 Sq.mm	Rmt	76		
<b>E-17</b>	Providing Indoor ordinary end terminations for the cable specified above with compression type steel gland, Bi-metallic lugs using crimping tool,Insulation tape,Identification tags etc., including end termination and Earthing of Gland with 8SWG 'GI Wire				
	a) 3.5C X 50 Sq.mm	No	2		
<b>E -18 Earthing</b>					
	a) Providing G.I. Earth station, with 40mm dia 2500mm longGI pipe including construction of brick pedestal, providing meshed funnel,Ci cover and other civil Engineering works,spreading a homogenous mixture of salt, charcoal aroundthe pipe etc, completely as per IS 3043, 1987 or latest revision.	No	1		

S.NO	DESCRIPTION	UNIT	QTY	Rate (Rs)	Amount(Rs)
	b) Providing Copper Earth station, with 600X600X3.15mm Copper plate at 2500mm depth including construction of brick pedestal, providing meshed funnel, CI cover and other civil Engineering works, spreading a homogenous mixture of salt, charcoal around the pipe etc, completely as per IS3043, 1987 or latest revision.	No	1		
	c) Supply and laying of following size strips including including all necessary inter connections with earth station and equipments.				
	i) 8 SWG Copper wire	Rmt	72		
<b>19</b>	<b><u>LAN Cable</u></b>				
<b>a</b>	Supply and Laying of 4Pair CAT-6E LAN Cable with suitable PVC Conduite and Junction boxes with etc.	Pts	10		
<b>b</b>	Supply and fixing of CAT-6E Information out lets Systimax/ Amps/ D Link	Set	10		
<b>c</b>	Supply of Patch Cards 3' (Factory Crimping)	Set	10		
<b>d</b>	Supply of Patch Cards 7' (Factory Crimping)	Set	10		
<b>e</b>	Supply and fixing of 24 port Jack panel (Systimax/ amp)	Set	1		
<b>f</b>	Supply and fixing of 9U Rack encloser with accries like Self Power manager, Cable Manager, Hard Ware etc.	Set	1		
<b>g</b>	Supply and fixing of 24 ports d-link switch	Set	1		
<b>20</b>	<b>Dismantalling of old wiring &amp; Providing Temporary Connections at the time of Renovations Period.</b>	LS	1		
<b>A</b>	<b>TOTAL AMOUNT FOR BRANCH ELECTRICAL WORKS Rs :</b>				
	<b>GST EXTRA</b>		<b>18%</b>		
	<b>Rupees</b>				